

GAZELLE

POWERplus<sup>®</sup>



CE ROHS<sup>✓</sup>

# The POWERplus® Gazelle PEDAL POWER GENERATOR AND AC/DC POWERBANK



Now you can enjoy the freedom of mobile energy everywhere !

The POWERplus® Gazelle is a pedal powered power generator with an AC/DC Powerbank. Now you have everywhere at any time power available by simply power generating by cycling by yourselves.

During cycling you charge the multifunction powerbank easily , so excersing and power generating at the same time !

The multifunctional powerbank includes a 12V internal battery and through the integrated inverter you can also select an ouput of 3V, 4.5V, 6V, 9V and 12V so it can almost always match your mobile devices for charging them.

Even an AC inverter is integrated in the powerbank so you can enjoy 220V power at max.100W.

To complete the powerbank is equipped with an integrated flashlight, storage space for adapters etc and an integrated handle for easy carrying and transportation



Multifunctional AC/DC Powerbank



Pedal power generation

## Technical details

Pedal Power Genetor output.	12 Volt / 900 mAh
Power station input	12 Volt / 900 mAh
Output DC Powerbank	3V, 4.5V 6V, 9V, 12V
AC Output Powerbank	220V / 100W
Time fully charged by cycling 60 rot./min	9 hours
Time fully charged by AC adapter	7-8 hours
Battery type	VRLA (lead acid)
Capacity of battery	12V, 7 Ah
Light function	5 of 9 LED's
Size	337 x 355 x 267 mm
Weight	4.8 kg
Indication of using time fully charged	
5 pcs. LED	85 hours
9 pcs. LED	40 hours
7W Saving Bulb	10 hours
15W CD player	4 hours
40W 14" TV	1.5 hours
70W Notebook	1 hour